

Krix Seismix Cube Series One
Active Subwoofer
Product Specifications



Krix Seismix Cube Series One Active Subwoofer.



Krix Seismix Cube Series One
Active Subwoofer
Product Specifications



Krix Seismix Cube Series One Active Subwoofer Description.

Boost your music listening experience or **add critical bass depth** to your home cinema with the Krix Seismix Cube. The Krix Seismix Cube's compact design is perfectly suited to environments with limited space.

The Krix Seismix Cube uses a 150 watt in-built amplifier, matched to a downward firing 200mm bass driver and vent, with the cabinet raised off the floor via specially moulded rubber isolation feet. This simple and effective styling ensures that the Krix Seismix Cube can be **placed almost anywhere** in your room, including custom joinery to deliver a small space, big bass experience.

The Krix Seismix Cube is part of the **Krix Series One** range of home theatre speakers, which also includes the Atomix bookshelf speakers, Rhythmix floor-standing front speakers, and Sonix centre channel speaker. These other Krix Series One speakers are the perfect sonic and aesthetic match for your Krix Seismix Cube subwoofer.





Krix Seismix Cube Active Subwoofer Specifications.

Frequency Range: 25Hz-200Hz useable in room response. Low pass filter 50 - 200Hz, 2nd order. High pass filter to limit driver excursion below 26Hz.

Bass Driver: Nominal 200mm (8") diameter doped paper cone driver, 38mm (1.5") voice coil wound on high powered aluminium former, with vented magnet assembly.

Amplifier Power: 150 Watts RMS into the nominal 4 Ohm driver, with a Maximum instantaneous power of 300 Watts.

Amplifier S/N Ratio: >85dB.

Distortion - Input to Speaker: <0.2% - @ 130 Watts RMS.

Line Level Inputs: Left Input (mono) – 130mV RMS for maximum output, or Left + Right Input (stereo) – 65mV RMS for maximum output.

Output: 116dB maximum SPL in room response.

Auto Power On/Off: 20 minute delay before switching to standby after no input signal.

Phase Select: 0° or 180° relative to the input signal.

Enclosure Type: Bass reflex, downward firing vent.

Dimensions: 375mm high x 295mm wide x 320mm deep.

Finish: High Gloss Black.

Weight: 11kg.

**Krix Seismix Cube Series One
Active Subwoofer**
Product Specifications



More Krix Seismix Cube Subwoofer Information:

Website Pages:

Krix Atomix Series One bookshelf speaker **website page**.

<http://www.cleverhome.com.au/products/Krix-bookshelf-speakers-Atomix-Series-One.shtml>

Krix Rhythmix Series One floor-standing speaker **website page**.

<http://www.cleverhome.com.au/products/Krix-floor-speakers-Rhythmix-Series-One.shtml>

Krix Sonix Series One centre speaker **website page**.

<http://www.cleverhome.com.au/products/Krix-centre-speakers-Sonix-Series-One.shtml>

Krix Seismix Cube Series One active subwoofer **website page**.

<http://www.cleverhome.com.au/products/Krix-active-subwoofer-Seismix-Cube-Series-One.shtml>

Reviews:

Krix Seismix Cube Series One subwoofer **Reviews**.

<http://www.krix.com.au/Product/Reviews.aspx?p=61&c=Seismix%20Cube&y=&t=#section->

Brochures and Manuals:

Krix Seismix Cube Series One subwoofer **Brochure**.

<http://www.cleverhome.com.au/automation/Krix-active-subwoofer-Seismix-Cube-Series-One.pdf>

Krix home theatre or stereo speaker **Owner Manual**.

<http://www.cleverhome.com.au/user/Krix-loudspeakers-owner-manual.pdf>

Where to buy Krix speakers in Victoria Australia.



Clever Home Pty Ltd

Phone (03) 9722 9210 Fax (03) 9733 1254

Clever Home Automation Website: www.cleverhome.com.au

Krix Speakers Clever Home Website Page